

Sensor Technical Specifications

Conductivity Sensor



Parameter measurement	conductivity, temperature
Measure range Conductivity:	0-2000us/cm Temperature: (0~50.0)°C
Accuracy Conductivity	±20 us/cm Temperature: ±0.5°C
Reaction time	<60S
Power supply	24VDC
Power dissipation	1W
Communication mode	RS485(Modbus RTU)